Chip Ferrite Bead Part Numbering

(Part Number)	BL	Μ	18	AG	102	S	Ν	1	D
	1	2	3	4	5	6	7	8	9
	Prod	uct ID							

Product ID	
BL	Chip Ferrite Beads

2Type

Code	Туре
Α	Array Type
М	Ferrite Bead Single Type

Obimensions (L×W)

Code	Dimensions (L×W)	EIA
02	0.4×0.2mm	01005
03	0.6×0.3mm	0201
15	1.0×0.5mm	0402
18	1.6×0.8mm	0603
2A	2.0×1.0mm	0804
21	2.0×1.25mm	0805
31	3.2×1.6mm	1206
41	4.5×1.6mm	1806

Output Characteristics/Applications

6Impedance

Expressed by three figures. The unit is in ohm ($\Omega)$ at 100MHz. The first and second figures are significant digits, and the third figure expresses the number of zeros that follow the two figures.

6 Electrode

Expressed by a letter.

•		
Ex.)	Code	Electrode
	S/T	Sn Plating
	А	Au Plating

Category

Code	Category
Ν	Standard Type

8Number of Circuits

Code	Number of Circuits
1	1 Circuit
4	4 Circuits

Code *1	Characteristics/Applications	Series
AG		BLM03/15/18/21, BLA2A/31
AX	For General Use	BLM02/03/15
TG		BLM18
BA		BLM15/18
BB		BLM03/15/18/21, BLA2A
BC	For High-speed Signal Lines	BLM03/15
BD		BLM03/15/18/21, BLA2A/31
BX		BLM02/15
PD		BLM15
PG	For Power Lines	BLM03/15/18/21/31/41
PX		BLM03/15
KG	For Power Lines (Low DC Resistance Type)	BLM18
SG	For Fower Lines (Low DC Resistance Type)	BLIVITO
RK	For Digital Interface	BLM18/21
HG	For GHz Band General Use	BLM03/15/18
EB	For GHz Band High-speed Signal Lines (Low Direct Current Type)	BLM03
EG	For GHz Band General Use (Low DC Resistance Type)	BLM15/18
HB		BLM03/15/18
HD	For GHz Band High-speed Signal Lines	BLM03/15/18
HE		BLM18
HK	For GHz Band Digital Interface	BLM18
GA	For High-GHz Band High-speed Signal Lines	BLM15
GG	For High-GHz Band General Use	BLM15/18

*1 Frequency characteristics vary with each code.

Continued on the following page.



Packaging

Code	Packaging	Series	
К	Embossed Taping (ø330mm Reel)	BLM21* ¹ /31/41	
L	Embossed Taping (ø180mm Reel)		
В	Bulk	All Series	
J	Paper Taping (ø330mm Reel)	BLM03/15/18* ³ /21* ² , BLA2A/31	
D	Paper Taping (ø180mm Reel)	BLM02/03/15/18/21* ² , BLA2A/31	

*1 BLM21BD222SN1/BLM21BD272SN1 only.
*2 Except for BLM21BD222SN1/BLM21BD272SN1
*3 Except for BLM18T

